

NE555 PWM Motor Speed Controller 13KHz 12-40VDC 10A



Technical parameters:

The input voltage: DC 12 v - 40 v

Power: 0.01 400 w

Current, rated current 8 A, through the current largest 10. A, static current 0.02 A (standby)

13 KHZ frequency:

The PWM pulse width speed range: 10% 100%

With 10 a fuse, with power control, voltage over-voltage protection function

With the high quality potentiometer

For positive & negative function, customers can external and switch.

Product specifications:

Size: 55 * 60 * 28 mm, four positioning hole is apart from the 5 mm plate edge, positioning hole diameter is 3.2 mm.

Weight: 69 g

Onboard 10 a fuse, the fuse is 5 * 20 mm standard size